

# Wireless Condenser Microphone

Portable PA System

0.55 lbs

**SENRUN®**

U H - 8 1 5



© Sunrise Trading Company

## SPECIFICATION

|                             |                    |
|-----------------------------|--------------------|
| <b>Microphone capsule</b>   | Condenser          |
| <b>Frequency range</b>      | 600 ~ 960MHz       |
| <b>Selectable channels</b>  | Preset 16 channels |
| <b>Antenna</b>              | ±0.005%            |
| <b>Frequency Stability</b>  | Built in           |
| <b>RF output power</b>      | Max. 10mW          |
| <b>Currency consumption</b> | 120mA ±10mA        |
| <b>Battery</b>              | 1.5V x 2 Pecs      |
| <b>Weight</b>               | 250 g              |